



CITEL

■■■ Reliability in Surge Protection ■■■

Surge Protection for Security Systems



All devices used in security system are based on integrated circuit that is highly susceptible and vulnerable to lightning and switching surges.


If these systems are damaged by a transient, then the entire protection strategy could be compromised : surge protection is highly recommended.

The cost of fully surge protecting a security system is limited and provides peace of mind that your system will be operational when you need it most.

CCTV CAMERAS




FIRE ALARM



SECURITY ROOM




ACCESS CONTROL



- RAK BNC
- RAK16-E-C6
- RAK16-POE-A



- DS240-230/G
- DS440-230/G
- MSB10-400
- DS220-12DC
- DS220-24DC
- DS230-48DC



- MSP
- UTPB
- DIN BNC
- DIN-E-C6
- CXC
- MJ8



- DLA-06D3
- DLA-12D3
- DLA-24D3
- DLA-48D3



Surge protectors for CCTV cameras

Combined CCTV surge protectors

The MSP-VM-2P series is designed to protect Pan Tilt Zoom security cameras connected to a CCTV network from transient over-voltages. It is a triple protection for video signal, 24 V or 230 Vac power supply and RS485 data signal lines.



Technical data	MSP-VM24-2P	MSP-VM230-2P
Max. video line voltage	6 Vdc	6 Vdc
Max. data line voltage	8 Vdc	8 Vdc
Max. power line voltage	30 Vac/Vdc	255 Vac
Nominal discharge current (In) 8/20μs impulse - 10 times	5kA/10kA (video)	5kA/10kA (video)

BNC surge protectors

This surge protector is designed to protect a single BNC coaxial line and can be used in multiline configuration in the RAK 16-BNC panel



Technical data	CXC06-B/FM
Max. line voltage	6 Vdc
Nominal discharge current (In) 8/20μs impulse - 10 times	10 kA
Connectors	BNC Female/Male

BNC surge protectors



Technical data	DIN-BNC
Nominal voltage line (DC)	6 Vdc
Nominal discharge current (In)	300 A
Connectors	BNC Female/Female

Video Balun surge protectors

UTPB-1 series is a single channel video balun with surge protection. They are used to interface DVR's, CCTV cameras and multiplexers.



Technical data	UTPB-1	UTPB-1J
Transmission signal	1 channel	1 channel
Transmission distance	up to 600 m	up to 600 m
Isolation voltage	4 kV	4 kV
Connectors	BNC-male 2 wires screw terminal	BNC-male jumper 2 wires screw terminal

CAT6 surge protectors



Technical data	DIN-E-C6
Max. line voltage	7.5 Vdc
Nominal discharge current (In)	400 A
Connectors	RJ45/RJ45


CAT5 and POE surge protectors



Technical data	MJ8-POE-A	MJ8-POE-B	MJ8-CAT5E
Max. line voltage	60 Vdc	7.5 Vdc (1,2,3,6) 60 Vdc (4,5,7,8)	8 Vdc
Nominal discharge current (In) (line/ground @ 8/20μs)	2 kA	2 kA	2kA
Connectors	Shielded RJ45	Shielded RJ45	Shielded RJ45

Surge protectors for Control Rooms

19" rack surge protectors



Technical data	RAK16-BNC	RAK16-E-C6	RAK16-POE-A
Number of ports	16	16	16
Maximum line voltage	7.5 Vdc	7.5 Vdc	60 Vdc
Nominal discharge current	300 A	400 A	300 A
Connectors	BNC	RJ45	RJ45

Surge protectors for Access Control and Fire Alarm System

AC surge protectors



Technical data	DS240-230/G	DS440-230/G	MSB10-400
AC network	230 V	230 V	230 V
Configuration	Single-phase	3-phase +N	Single-phase
Max. operating voltage	255 V	255 V	255 V
Nominal discharge current	20 kA	20 kA	3 kA
Maximum discharge current	40 kA	40 kA	10 kA
Wiring	Screw terminal	Screw terminal	Wires
Mounting	DIN rail	DIN rail	Wall/Flange
Remote signalling	Option	Option	No

DC surge protectors



Technical data	DS220-12DC	DS220-24DC	DS230-48DC
Nominal DC voltage	12 Vdc	24 Vdc	48 Vdc
Max. operating voltage	24 Vdc	38 Vdc	65 Vdc
Nominal discharge current	10 kA	10 kA	20 kA
Maximum discharge current	20 kA	20 kA	30 kA
Wiring	Screw terminal	Screw terminal	Screw terminal
Mounting	DIN rail	DIN rail	DIN rail
Remote signalling	Option	Option	Option

Dataline surge protectors



Technical data	DLA-06D3	DLA-12D3	DLA-24D3	DLA-48D3
Typical application	RS422	RS232/RS485	4-20mA	48 V line
Configuration	1pair+shield	1 pair+shield	1 pair+shield	1 pair+shield
Nominal line voltage	6 V	12 V	24 V	48 V
Max. line current	300 mA	300 mA	300 mA	300 mA
Nominal discharge current	5 kA	5 kA	5 kA	5 kA
Maximum discharge current	20 kA	20 kA	20 kA	20 kA
Mounting	DIN rail	DIN rail	DIN rail	DIN rail



CITEL

■■■ Reliability in Surge Protection ■■■

Head office

CITEL-2CP

2, rue Troyon
92316 Sèvres CEDEX
France
Tél. : +33 1 41 23 50 23
Fax : +33 1 41 23 50 09
e-mail : contact@citel.fr
Web : www.citel.fr

Factory

CITEL-2CP

3 impasse de la Blanchisserie
BP 56
51052 Reims CEDEX
France
Tél. : +33 3 26 85 74 00
Fax : +33 3 26 85 74 30

Germany

CITEL Electronics GmbH

Alleestrasse 144, Tor 5
D-44793 Bochum
Germany
Tél. : +49 234 54 72 10
Fax : +49 234 54 72 199
e-mail : info@citel.de
Web : www.citel.de

USA

CITEL Inc.

10108 USA Today Way
Miramar, FL33025
USA
Tel : (954) 430 6310
Fax : (954) 430 7785
e-mail : info@citel.us
Web site : www.citel.us

China

Shanghai Citel Electronics Co.,Ltd

499 Kang Yi Road
Kang Qiao Industrial Zone
201315 Pudong, Shanghai
P.R. CHINA
Tél. : +86 21 58 12 25 25
Fax : +86 21 58 12 21 21
e-mail : shanghai@citel2cp.com
Web : www.citel.cn

Czech Republic

CITEL ELECTRONICS

Kundratka 17A
18000 Praha
Czech Republic
Tél. : +420 284840-395
Fax : + 420 284840-195
e-mail : citel@citel.cz
Web : www.citel.cz

Russia

CITEL RUSSIA

Bolchaya Pochtovaya Str 26B/1
RU-105082 Moscow
Russia
Tél. : +7 495 669 32 70
e-mail : info@citel.ru
Web : www.citel.ru

India

CITEL INDIA

A - 54 - South Extension, Part-II
New Delhi - 110049
India
Tél. : +91 11 2626 12 38
e-mail : indiacitel@gmail.com
Web : www.citel.in

BR121202A - Document could be modified without notice